Let us entertain you











With its beautiful high gloss finish, the Jamo P 404 has a visual identity tailored for the way we listen to music today.

Further the P 404 can be connected to a multiple number of sources, just as you would expect from the loudspeaker-systems of today. 4 different inputs allows you to listen to TV, PC, Laptop, phone or whatever you fancy, and the input of choice can be selected through the remote control. Wireless connectivity is also an option, with a USB-5V-port giving charge to the Jamo WK-200 wireless kit. The USB-port can also be used to charge your iPhone/iPod.

Using a 5½" woofer and a 1" soft dome tweeter coupled directly to a capable amplifier (2 x 30W) the P 404 is certainly able to pack a punch in any modern living room.
But for those that enjoy further entertainment it is possible to connect a subwoofer in order to get the fundamentals right.

No matter what you choose to do the Jamo P 404 will know when it's over: it will automatically go into standby after 10 minutes without signal.

Specifications	**P 404**
System	2.0 Active Bassreflex (Left Active + Right Passive)
Amplifier Rated Output (Watt)	2x30W @4Ohm @1%THD
Woofer (mm / in)	140 / 5½
Tweeter (mm / in)	25 / 1 Soft dome
Frequency Range (Hz)	50 - 20.000 @ +/- 3dB
Input: Optical	2
Input: AUX1 (RCA)	1
Input: AUX2 (3,5mm Minijack)	1
Output: Sub out	1
LED Indicator	On/Signal Blue
	Off/Standby Red (Switches off after 10 min.)
	Mute Red (Flashing)
	RC operation is valid (Blue flickering)
Tone Control	Bass: +/-6dB @ 100Hz, default 0dB
	Treble: +/-6dB @ 1000kHz, default 0dB
	Reset: Bass and Treble return to 0dB
USB 5V Charge	1
Stand-by power (Watt)	<1.0
Weight P 404 Left (kg/lb)	5,1 / 11.24
Weight P 404 Rigth (kg/lb)	3,6 / 7.93
Dimensions (mm / in)	240 x 162 x 218 / 9.44 x 6.37 x 8.58
Finishes	HG Black or HG White



Jamo®
Danish Sound Design

16.08.2011